ON Semiconductor

Is Now



To learn more about onsemi™, please visit our website at www.onsemi.com

onsemi and ONSEMI. and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. onsemi reserves the right to make changes at any time to any products or information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/ or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use onsemi products for any such unintended or unauthorized application,

Self-Protected Low Side Driver with In-Rush Current Management

The NCV8411 is a three terminal protected Low–Side Smart Discrete FET. The protection features include Delta Thermal Shutdown, overcurrent, overtemperature, ESD and integrated Drain to Gate clamping for over voltage protection. The device also offers fault indication via the gate pin. This device is suitable for harsh automotive environments.

Features

- Short Circuit Protection with In-Rush Current Management
- Delta Thermal Shutdown
- Thermal Shutdown with Automatic Restart
- Over Voltage Protection
- Integrated Clamp for Over Voltage Protection and Inductive Switching
- ESD Protection
- dV/dt Robustness
- Analog Drive Capability (Logic Level Input)
- NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC-Q101 Qualified and PPAP Capable
- These Devices are Pb-Free and are RoHS Compliant

Typical Applications

- Switch a Variety of Resistive, Inductive and Capacitive Loads
- Can Replace Electromechanical Relays and Discrete Circuits
- Automotive / Industrial




Figure 1. Block Diagram

1



ON Semiconductor®

www.onsemi.com

V _{DSS} (Clamped)	R _{DS(ON)} TYP	I _D MAX (Limited)
42 V	23 mΩ @ 10 V	45 A



CASE 369C STYLE 2

MARKING DIAGRAM

1 = Gate	1 🗁	AYWW	h
2 = Drain	2 🗖	NCV	
3 = Source	3 🗀	8411G	V

A = Assembly Location

Y = Year WW = Work Week G = Pb-Free Package

ORDERING INFORMATION

Device	Package	Shipping [†]
NCV8411DTRKG	DPAK (Pb-Free)	2500/Tape & Reel

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specification Brochure, BRD8011/D.

Table 1. MAXIMUM RATINGS

Rating	Symbol	Value (min)	Unit
Drain-to-Source Voltage Internally Clamped	V _{DSS}	42	V
Drain-to-Gate Voltage Internally Clamped	V_{DG}	42	V
Gate-to-Source Voltage	V _{GS}	±14	V
Drain Current - Continuous	I _D	Internally Lin	nited
Total Power Dissipation @ T _A = 25°C (Note 1) @ T _A = 25°C (Note 2)	P _D	1.3 2.7	W
Thermal Resistance Junction-to-Case Junction-to-Ambient (Note 1) Junction-to-Ambient (Note 2)	R _{thJC} R _{thJA} R _{thJA}	0.65 95 45	°C/W
Single Pulse Inductive Load Switching Energy (Note 3) $(L = 120 \text{ mH}, T_{J(start)} = 150^{\circ}\text{C})$	E _{AS}	600	mJ
Load Dump Voltage (VGS = 0 and 10 V, RG = 2 Ω , RL = 3 Ω) (Note 4)	U _S *	55	V
Operating Junction Temperature	T _J	-40 to 150	°C
Storage Temperature	T _{storage}	-55 to 150	°C
ESD CHARACTERISTICS (Note 3)			-
Electro-Static Discharge Capability Human Body Model (HBM)	ESD	4	kV

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

- Mounted onto a 2" square FR4 board (100 sq mm, 1 oz. Cu, steady state)
 Mounted onto a 2" square FR4 board (645 sq mm, 1 oz. Cu, steady state)
- 3. Not tested in production.
- Load Dump Test B (with centralized load dump suppression) according to ISO16750–2 standard. Guaranteed by design. Not tested in production. Passed Class C according to ISO16750–1.





Figure 2. Voltage and Current Convention

Table 2. ELECTRICAL CHARACTERISTICS (T $_{J}$ = $25^{\circ}C$ unless otherwise noted)

Characteristic	Test Conditions	Symbol	Min	Тур	Max	Unit
OFF CHARACTERISTICS						
Drain-to-Source Clamped	$V_{GS} = 0 \text{ V}, I_D = 250 \mu\text{A}$	V _{(BR)DSS}	42	46	50	V
Breakdown Voltage	$V_{GS} = 0 \text{ V, } I_D = 250 \mu\text{A,}$ $T_J = 150^{\circ}\text{C (Note 5)}$		42	44	50	
Zero Gate Voltage Drain Current	V _{DS} = 32 V, V _{GS} = 0 V	I _{DSS}	-	1.5	5	μΑ
	V _{DS} = 32 V, V _{GS} = 0 V, T _J = 150°C (Note 5)		-	5.5	-	
Gate Input Current	$V_{GS} = 5 \text{ V}, V_{DS} = 0 \text{ V}$	I_{GSS}	-	50	100	μΑ
ON CHARACTERISTICS						
Gate Threshold Voltage	$V_{GS} = V_{DS}$, $I_D = 1.2 \text{ mA}$	V _{GS(th)}	1.0	1.8	2.5	V
Threshold Temperature Coefficient	$V_{GS} = V_{DS}$, $I_D = 1.2 \text{ mA (Note 5)}$		-	5	-	mV/°C
Static Drain-to-Source	$V_{GS} = 10 \text{ V}, I_D = 5 \text{ A}, T_J = 25^{\circ}\text{C}$	R _{DS(ON)}	-	23	29	mΩ
On Resistance	V _{GS} = 10 V, I _D = 5 A, T _J = 150°C (Note 5)		-	43	55	
	$V_{GS} = 5 \text{ V}, I_D = 5 \text{ A}, T_J = 25^{\circ}\text{C}$		-	28	34	1
	V _{GS} = 5 V, I _D = 5 A, T _J = 150°C (Note 5)		-	50	60	
Source Drain Forward On Voltage	$I_S = 5 A, V_{GS} = 0 V$	V_{SD}	-	0.8	1.1	V
SWITCHING CHARACTERISTICS (No	ote 5)					
Turn-On Time (10% V_{GS} to 90% I_D)	$V_{GS} = 0 \text{ V to 5 V},$	t _{ON}	-	29	50	μs
Turn-Off Time (90% V_{GS} to 10% I_D)	$V_{DS} = 12 \text{ V}, I_{D} = 1 \text{ A}$	t _{OFF}	-	53	150	1
Turn-On Time (10% V_{GS} to 90% I_D)	$V_{GS} = 0 \text{ V to } 10 \text{ V},$	t _{ON}	-	14	25	
Turn-Off Time (90% V_{GS} to 10% I_{D})	$V_{DS} = 12 \text{ V}, I_D = 1 \text{ A}$	t _{OFF}	ı	80	180	
Slew Rate On (80% V_{DS} to 50% V_{DS})	$V_{GS} = 0 \text{ V to } 10 \text{ V},$	$-dV_{DS}/dt_{ON}$	-	1.52	2.5	V/μs
Slew Rate Off (50% V_{DS} to 80% V_{DS})	$V_{DD} = 12 \text{ V}, R_L = 4.7 \Omega$	dV _{DS} /dt _{OFF}	-	0.71	0.85	
SELF PROTECTION CHARACTERIST	rics					
Current Limit	$V_{GS} = 5 \text{ V}, V_{DS} = 10 \text{ V}$	I _{LIM}	29	33	40	Α
	$V_{GS} = 5 \text{ V}, V_{DS} = 10 \text{ V},$ $T_J = 150^{\circ}\text{C (Note 5)}$		27	31	37	
	V _{GS} = 10 V, V _{DS} = 10 V (Note 5)		23	34	46	
	$V_{GS} = 10 \text{ V}, V_{DS} = 10 \text{ V},$ $T_{J} = 150^{\circ}\text{C (Note 5)}$		23	33	46	
Temperature Limit (Turn-Off)	V _{GS} = 5 V (Note 5)	T _{LIM(OFF)}	150	170	185	°C
Thermal Hysteresis		$\Delta T_{LIM(ON)}$	-	10	_	1
Temperature Limit (Turn-Off)	V _{GS} = 10 V (Note 5)	T _{LIM(OFF)}	150	180	200	
Thermal Hysteresis		$\Delta T_{LIM(ON)}$	_	10	_	
GATE INPUT CHARACTERISTICS (N	ote 5)					
Device ON Gate Input Current –	$V_{GS} = 5 \text{ V}, V_{DS} = 10 \text{ V}, I_D = 1 \text{ A}$	I _{GON}	-	50	100	μΑ
Normal Operation	V _{GS} = 10 V, V _{DS} = 10 V, I _D = 1 A		200	318	500	
Device ON Gate Input Current –	$V_{GS} = 5 \text{ V}, V_{DS} = 10 \text{ V}, I_D = 0 \text{ A}$	I_{GTL}	_	633	900	
Thermal Limit	$V_{GS} = 10 \text{ V}, V_{DS} = 10 \text{ V}, I_D = 0 \text{ A}$		_	1470	2000	
Device ON Gate Input Current –	$V_{GS} = 5 \text{ V}, V_{DS} = 10 \text{ V}$	I _{GCL}	-	245	600	
Current Limit	$V_{GS} = 10 \text{ V}, V_{DS} = 10 \text{ V}$		-	1121	1500	

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.


5. Not tested in production.



10000 T_{J(start)} = 25°C 1000 T_{J(start)} = 150°C 100 L (mH)

Figure 3. Single Pulse Maximum Switch-off Current vs. Load Inductance

Figure 4. Single Pulse Maximum Switching Energy vs. Load Inductance







Figure 5. Single Pulse Maximum Inductive Switch-off Current vs. Time in Avalanche

Figure 6. Single Pulse Maximum Inductive Switching Energy vs. Time in Avalanche






Figure 7. On-state Output Characteristics at 25°C

Figure 8. Transfer Characteristics




Figure 9. R_{DS(on)} vs. Gate-Source Voltage




Figure 10. R_{DS(on)} vs. Drain Current




Figure 11. Normalized R_{DS(on)} vs. Temperature




Figure 12. Current Limit vs. Gate-Source Voltage




Figure 13. Current Limit vs. Junction Temperature




Figure 14. Drain-to-Source Leakage Current




Figure 15. Normalized Threshold Voltage vs. Temperature




Figure 16. Source-Drain Diode Forward Characteristics




Figure 17. Resistive Load Switching Time vs.
Gate-Source Voltage




Figure 18. Resistive Load Switching Drain-Source Voltage Slope vs. Gate-Source Voltage




Figure 19. Resistive Load Switching Time vs.
Gate Resistance




Figure 20. Drain-Source Voltage Slope during Turn On and Turn Off vs. Gate Resistance




Figure 21. $R_{\theta JA}$ vs. Copper Area




Figure 22. Transient Thermal Resistance

APPLICATION INFORMATION

Circuit Protection Features

The NCV8411 has three main protections. Current Limit, Thermal Shutdown and Delta Thermal Shutdown. These protections establish robustness of the NCV8411.

Current Limit and Short Circuit Protection

The NCV8411 has current sense element. In the event that the drain current reaches designed current limit level, integrated Current Limit protection establishes its constant level.

Delta Thermal Shutdown

Delta Thermal Shutdown (DTSD) Protection increases higher reliability of the NCV8411. DTSD consist of two independent temperature sensors – cold and hot sensors. The

NCV8411 establishes a slow junction temperature rise by sensing the difference between the hot and cold sensors. ON/OFF output cycling is designed with hysteresis that results in a controlled saw tooth temperature profile (Figure 23). The die temperature slowly rises (DTSD) until the absolute temperature shutdown (TSD) is reached around 175°C.

Thermal Shutdown with Automatic Restart

Internal Thermal Shutdown (TSD) circuitry is provided to protect the NCV8411 in the event that the maximum junction temperature is exceeded. When activated at typically 175°C, the NCV8411 turns off. This feature is provided to prevent failures from accidental overheating.

TEST CIRCUITS AND WAVEFORMS




Figure 23. Overload Protection Behavior

TEST CIRCUITS AND WAVEFORMS




Figure 24. Resistive Load Switching Test Circuit




Figure 25. Resistive Load Switching Waveforms

TEST CIRCUITS AND WAVEFORMS




Figure 26. Inductive Load Switching Test Circuit





Figure 27. Inductive Load Switching Waveform

ROTATED 90° CW

STYLE 1:

STYLE 2:





DATE 21 JUL 2015

- IOTES. 1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. 2. CONTROLLING DIMENSION: INCHES. 3. THERMAL PAD CONTOUR OPTIONAL WITHIN DI-

- MENSIONS b3, L3 and Z.


 Jimensions b And E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR BURRS. MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED 0.006 INCHES PER SIDE.

 MENSIONS D AND E ARE DETERMINED AT THE
- OUTERMOST EXTREMES OF THE PLASTIC BODY.

 6. DATUMS A AND B ARE DETERMINED AT DATUM
- 7. OPTIONAL MOLD FEATURE.

	INCHES		MILLIM	IETERS
DIM	MIN	MAX	MIN	MAX
Α	0.086	0.094	2.18	2.38
A1	0.000	0.005	0.00	0.13
b	0.025	0.035	0.63	0.89
b2	0.028	0.045	0.72	1.14
b3	0.180	0.215	4.57	5.46
С	0.018	0.024	0.46	0.61
c2	0.018	0.024	0.46	0.61
D	0.235	0.245	5.97	6.22
E	0.250	0.265	6.35	6.73
е	0.090	BSC	2.29	BSC
Н	0.370	0.410	9.40	10.41
L	0.055	0.070	1.40	1.78
L1	0.114	REF	2.90 REF	
L2	0.020	BSC	0.51 BSC	
L3	0.035	0.050	0.89	1.27
L4		0.040	1.01	
Z	0.155		3.93	

GENERIC MARKING DIAGRAM*



XXXXXX = Device Code = Assembly Location Α = Wafer Lot L

Υ = Year WW = Work Week G = Pb-Free Package

*This information is generic. Please refer to device data sheet for actual part marking.

В L3 Ζ Ո DETAIL A NOTE 7 **BOTTOM VIEW** Cb2 е SIDE VIEW | \oplus | 0.005 (0.13) lacktriangle C **TOP VIEW** Z Ħ L2 GAUGE C SEATING PLANE **BOTTOM VIEW** Α1 ALTERNATE CONSTRUCTIONS **DETAIL A**


3. EMITTER	3. SOURCE	 ANODE CATHODE 	3. GATE	3. CATHODE
4. COLLECTOR	4. DRAIN		4. ANODE	4. ANODE
3. GATE 3. EMI	LECTOR 2. TTER 3.	N/C PIN CATHODE ANODE	E 9: 1. ANODE 2. CATHODE 3. RESISTOR ADJUST 4. CATHODE	STYLE 10: PIN 1. CATHODE 2. ANODE 3. CATHODE 4. ANODE

STYLE 4:

STYLE 5:

STYLE 3:

SOLDERING FOOTPRINT*



*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

DESCRIPTION:	DPAK SINGLE GAUGE SURFACE MOUNT		PAGE 1 OF 2
NEW STANDARD:	REF TO JEDEC TO-252	"CONTROLLED COPY" in red.	
STATUS:	ON SEMICONDUCTOR STANDARD	accessed directly from the Document versions are uncontrolled except	
DOCUMENT NUMBER:	98AON10527D		



DOCUMENT	NUMBER:
98AON10527	7D

PAGE 2 OF 2

	,	
ISSUE	REVISION	DATE
0	RELEASED FOR PRODUCTION. REQ. BY L. GAN	24 SEP 2001
Α	ADDED STYLE 8. REQ. BY S. ALLEN.	06 AUG 2008
В	ADDED STYLE 9. REQ. BY D. WARNER.	16 JAN 2009
С	ADDED STYLE 10. REQ. BY S. ALLEN.	09 JUN 2009
D	RELABELED DRAWING TO JEDEC STANDARDS. ADDED SIDE VIEW DETAIL A. CORRECTED MARKING INFORMATION. REQ. BY D. TRUHITTE.	29 JUN 2010
E	ADDED ALTERNATE CONSTRUCTION BOTTOM VIEW. MODIFIED DIMENSIONS b2 AND L1. CORRECTED MARKING DIAGRAM FOR DISCRETE. REQ. BY I. CAMBALIZA.	06 FEB 2014
F	ADDED SECOND ALTERNATE CONSTRUCTION BOTTOM VIEW. REQ. BY K. MUSTAFA.	21 JUL 2015

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

ON Semiconductor and the are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor and see no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:
Email Requests to: orderlit@onsemi.com

ON Semiconductor Website: www.onsemi.com

TECHNICAL SUPPORT North American Technical Support: Voice Mail: 1 800-282-9855 Toll Free USA/Canada Phone: 011 421 33 790 2910

Europe, Middle East and Africa Technical Support:

Phone: 00421 33 790 2910

For additional information, please contact your local Sales Representative